

### IQ4 SPECS

BATTERY VOLTAGE	BULK STAGE	ABSORPTION STAGE	FLOAT STAGE
12V	14.8V	14.2V	13.6
24V	29.6V	28.4V	27.2V
48V*	59.2V	56.8V	54.4V

### IQ-AGM

Figure C: LED Code Table

LED CODE TABLE		
CELL INDICATION		
6 FLASHES	12V Battery	
12 FLASHES	24V Battery	
CHARGE PHASE	LED STATUS	VOLTAGE 12-VOLT / 24-VOLT
FLOAT	ON	13.6 / 27.2
BULK / FINISH	FLASHING	14.7 / 29.4

### IQ-GEL

LED CODE TABLE		
CELL INDICATION		
6 FLASHES	12V Battery	
12 FLASHES	24V Battery	
CHARGE PHASE	LED STATUS	VOLTAGE 12-VOLT / 24-VOLT
FLOAT	ON	13.6 / 27.2
BULK	RAPID FLASHING	14.23 / 28.46

### IQ-TURBO

LED CODE TABLE		
CELL INDICATION		
6 FLASHES	12V Battery (6 cells)	
12 FLASHES	24V Battery (12 cells)	
CHARGE PHASE	LED STATUS	VOLTAGE 12-VOLT / 24-VOLT
FLOAT	ON	13.6 / 27.2
ABSORPTION	SLOW FLASHING	14.51 / 29.02
BULK	RAPID FLASHING	14.78 / 29.56

### IQ-40HR

LED CODE TABLE		
CELL INDICATION		
6 FLASHES	12V Battery	
12 FLASHES	24V Battery	
CHARGE PHASE	LED STATUS	VOLTAGE 12-VOLT / 24-VOLT
FLOAT	ON	13.6 / 27.2
BULK	RAPID FLASHING	14.8 / 29.6

### IQ-EQUALIZER

LED CODE TABLE		
CELL INDICATION		
6 FLASHES	12V Battery (6 cells)	
12 FLASHES	24V Battery (12 cells)	
CHARGE PHASE	LED STATUS	VOLTAGE 12-VOLT / 24-VOLT
BULK	RAPID FLASHING	15.41 / 30.82
FLOAT	ON	13.6 / 27.2

### IQ-LIFEPO

LED CODE TABLE		
CELL INDICATION		
6 FLASHES	12V Battery	
12 FLASHES	24V Battery	
CHARGE PHASE	LED STATUS	VOLTAGE 12-VOLT / 24-VOLT
FLOAT	ON	13.6 / 27.2
BULK	RAPID FLASHING	14.7 / 29.4